

ST01C Timer Quick Instruction Guide:

- 1) Press the MODE button until you have PGM with the current time of day on the screen, press ON/OFF one time. This will bring you to setting #1.
- 2) Press ON/OFF again and the word ON should start flashing. (If you see OFF or SKIP flashing, press and release the + button until you see ON flashing.)
- 3) Press ON/OFF again and the word DUSK should start flashing. If you see DAWN or a fixed time, press + button until you get back to DUSK. If you want the lights to turn on at sunset, go to step 4.
 - 3a) If you want them to turn on at a set time every day, press the + button until you see 12:00 flashing on the screen. Press ON/OFF and the 12 should start flashing. Use the + button to adjust the hour for the time you want the lights to turn on. Press ON/OFF again and the minutes should flash. Use the + to set to the correct minutes for your turn on time.
- 4) Press ON/OFF again and the word ALL should start flashing. This will set this ON time for all 7 days of the week. If it does not say ALL, use the + button to set it for ALL.
- 5) Press ON/OFF again and the word SAVE will flash on the screen, then it will go back to your on time and 01 will start flashing at the bottom.
- 6) Press the + button to move to setting #2.
- 7) Press ON/OFF and the word OFF should start flashing. (If you see ON or SKIP flashing, press and release the + button until you see OFF flashing.) If your setting is correct, go to step 11.
- 8) Press ON/OFF again and the word DAWN should start flashing. If you want the lights to turn off at sunrise, go to step 9.
 - 8a) If you want them to turn of at a set time every day, press the + button until you see 12:00 flashing on the screen. Press ON/OFF and the 12 should start flashing. Use the + button to adjust the hour for the time you want the lights to turn off. Press ON/OFF again and the minutes should flash. Use the + to set to the correct minutes for your turn off time.
- 9) Press ON/OFF again and the word ALL should start flashing. This will set this OFF time for all 7 days of the week. If it does not say ALL, use the + button to set it for ALL.
- 10) Press ON/OFF again and the word SAVE will flash on the screen, then it will go back to your off time and 02 will start flashing at the bottom.
- 11) If additional ON/OFF times are needed, press the + button one time to move to the next setting, then repeat steps 2-11 for all additional settings.
- 12) Press the MODE button one time to go to AUTO mode.

Connect with Us

